

# Discussion 11B

## 1. Minimum Energy Control & Spectral Theorem

In controllability/reachability analysis, we try to solve the linear system:

$$C_{i^*} \begin{bmatrix} \vec{u}[0] \\ \vdots \\ \vec{u}[i^* - 1] \end{bmatrix} = \vec{x}^* - A^{i^*} \vec{x}_0 \quad (1)$$

for the vector quantities  $\vec{u}[0], \dots, \vec{u}[i^* - 1]$ . Cleaning up notation, let us fix  $i^*$ , let  $C := C_{i^*}$ , let  $\vec{z} := \vec{x}^* - A^{i^*} \vec{x}_0$ , and let  $\vec{u} := \begin{bmatrix} \vec{u}[0] \\ \vdots \\ \vec{u}[i^* - 1] \end{bmatrix}$ . Then this linear system becomes

$$C\vec{u} = \vec{z} \quad (2)$$

In the real world, we would like to use this framework to control mechanical systems, often expending the **minimum energy** possible.

But what do we mean by the "energy" of the control? In this context, we will use the squared norm of the input vector  $\|u\|^2 = u_1^2 + \dots + u_n^2$  as the model for the cost to applying a set of controls to our system.

Why do we use this definition? This formula for the cost model is closely connected to many physical scenarios relating to energy. Consider a few examples below:

- $E_{\text{capacitor}} = \frac{1}{2}CV^2$
- $E_{\text{spring}} = \frac{1}{2}kx^2$
- $E_{\text{kinetic}} = \frac{1}{2}mv^2$

And so we find that the definition we use is a natural one.

*Optional EECS16A Refresher: Recall the following vector spaces:*

*The range (or column space) of a matrix  $A$  refers to the following vector space  $\text{Col}(A) = \{A\vec{x} : \vec{x} \in \mathbb{R}^n\}$ . It is the vector space consisting of all possible linear combinations of the columns of  $A$ .*

*Then, there is the null space of  $A$ , which refers to the following vector space  $\text{Null}(A) = \{\vec{x} : A\vec{x} = 0\}$ .*

- (a) Suppose we would like to solve for the minimum energy (or minimum norm) solution of the linear system  $C\vec{u} = \vec{z}$ . This problem can be expressed as the following optimization problem:

$$\operatorname{argmin}_{\vec{u}} \|\vec{u}\|^2 = \operatorname{argmin}_{u[i]} \sum_{i=0}^{\ell-1} u[i]^2 \quad (3)$$

$$\text{s.t. } C\vec{u} = \vec{z} \quad (4)$$

Symmetric matrices can make calculations and reasoning about the properties of a matrix much easier. Suppose  $C$  is a *real, symmetric matrix*. **Rewrite  $C$  in terms of its spectral decomposition** (take  $Q$  to be the orthonormal basis of eigenvectors of  $C$  and  $\Lambda$  to be the diagonal matrix of the eigenvalues).

- (b) One way to look at minimum energy control is through lens of our vector spaces. How might we do this?

Well, Spectral Theorem tells us that  $Q$  is an orthonormal basis of  $\mathbb{R}^n$ . If  $\text{Rank}(C) = r$ , then  $Q$  can be written as the block matrix  $\begin{bmatrix} Q_r & Q_{n-r} \end{bmatrix}$  where  $Q_r$  forms an orthonormal basis for  $\text{Col}(C)$  and  $Q_{n-r}$  similarly forms one for  $\text{Null}(C)$ .

Let's perform an orthonormal basis change:

$$\vec{u} = Q\tilde{\vec{u}} \quad (5)$$

**Using our new basis, rewrite  $\vec{u}$  in terms of  $Q_r$  and  $Q_{n-r}$ .**

(HINT: Consider breaking up  $Q$  and  $\vec{u}$  into a block matrix and partitioned vector respectively.)

- (c) Ultimately, the objective we are trying to minimize is still  $\|\vec{u}\|^2$ . **Use your findings from part (b) to show that**  $\|\vec{u}\|^2 = \|\tilde{\vec{u}}_{\text{Col}(C)}\|^2 + \|\tilde{\vec{u}}_{\text{Null}(C)}\|^2$ .

(HINT: Given some arbitrary orthonormal matrix  $U$  and arbitrary vector  $\vec{p}$ , how are  $\|\vec{p}\|$  and  $\|U\vec{p}\|$  related?)

- (d) Putting everything from the last two parts together, let us now solve for the solution to the minimum energy problem (written once more for convenience):

$$\underset{\vec{u}}{\operatorname{argmin}} \|\vec{u}\|^2 = \underset{u[i]}{\operatorname{argmin}} \sum_{i=0}^{\ell-1} u[i]^2 \quad (6)$$

$$\text{s.t. } C\vec{u} = \vec{z} \quad (7)$$

**Solve for the optimal minimum energy input  $\vec{u}^*$  in its simplest form in terms of  $\vec{u}_{\text{Col}(C)}$  and/or  $\vec{u}_{\text{Null}(C)}$ . Explain what your result means intuitively.**

(HINT: Which of  $\vec{u}_{\text{Col}(C)}$  or  $\vec{u}_{\text{Null}(C)}$  doesn't effect  $C\vec{u}$  (try to think about your vector space definitions)? What should we do to that value if we want to minimize the squared norm of the input?)

(e) Now, let's do a numerical example. Consider the following linear discrete time system

$$\vec{x}[i + 1] = \begin{bmatrix} -1 & 0 \\ 0 & -1 \end{bmatrix} \vec{x}[i] + \begin{bmatrix} -1 \\ 1 \end{bmatrix} u[i] \quad (8)$$

**Find the controllability matrix  $C$  for this system.**

(f) Now, suppose we want to achieve desired state of  $\vec{x}[2] = \begin{bmatrix} 4 \\ -4 \end{bmatrix}$  at timestep  $i = 1$ . Assume your initial condition is  $\vec{x}[0] = \begin{bmatrix} 0 \\ 0 \end{bmatrix}$ .

**Write your linear system to solve for the input vector  $\vec{u} = \begin{bmatrix} \vec{u}[0] \\ \vec{u}[1] \end{bmatrix}$  in the form  $C\vec{u} = \vec{z}$ . Then, solve for one  $\vec{u}$  that achieves the desired system state.** Remember, there will be many solutions as the system is underdetermined.

*(HINT: Make use of the linear system formulation that comes as a result of controllability analysis shown on page 1.)*

(g) Finally, notice that  $\text{Col}(C) = \text{span} \left\{ \begin{bmatrix} 1 \\ -1 \end{bmatrix} \right\}$  and  $\text{Null}(C) = \text{span} \left\{ \begin{bmatrix} 1 \\ 1 \end{bmatrix} \right\}$ .

The minimum norm solution is  $\vec{u}_{\min} = \begin{bmatrix} 2 \\ -2 \end{bmatrix}$ . We will compare this to another arbitrary solution

$$\begin{bmatrix} 3 \\ -1 \end{bmatrix}.$$

i Write both  $\vec{u}_{\min}$  and  $\begin{bmatrix} 3 \\ -1 \end{bmatrix}$  as a linear combination of the column and null space span vectors. Compare the coefficients of the null space span vector.

ii Compare the norms of the two solutions. Verify that  $\|\vec{u}_{\min}\|$  is smaller.

**Contributors:**

- Anant Sahai.
- Nathan Lambert.
- Kareem Ahmad.
- Neelesh Ramachandran.
- Chancharik Mitra.
- Nikhil Jain.